

868MHz External Omni-directional Rubber Ducky Antenna

Model Number: SER-C868-5N

Applications:

- Low Power Radio (Sigfox, LPWA, LoRa)
- mesh networks
- IoT, metering, industrial/environmental Monitoring, remote asset monitoring

Features:

- Omnidirectional Radiation Pattern
- Compact and Easy to Store
- Vertical Polarization



| | |
|----------------------|----------------------|
| Type | Rubber Ducky Antenna |
| Model No. | SER-C868-5N |
| ELECTRICAL | |
| Frequency | 860-930MHz |
| Gain | 5dBi |
| VSWR | ≤1.5 |
| Radiation Properties | Omnidirectional |
| Power Handling | 20W |
| Polarization | Vertical |
| Impedance | 50 Ohms |
| MECHANICAL | |
| Length | 201mm |
| Weight | 38g |
| Connector | N Male |
| Color | Black |
| ENVIRONMENTAL | |
| Temperature Range | -40°C to 60°C |